

sFAB-a (alpha) Specifications

Machine		sFAB-a
Panel size (L x W)		80 x 50 mm to 508 x 330 mm
Part type quantity		Up to 20 part types
Lead diameter	Axial parts	φ0.4 to 0.8 mm
	Radial parts	φ0.4 to 0.8 mm
	Jumper wire	φ0.6 mm
Insertion pitch	Axial parts	5 to 20.32 mm
	Radial parts	2.5, 5.0 or 7.5 mm
	Jumper wire	5 to 20.32 mm
Part packaging	Axial parts	Ammo packs
	Radial parts	Ammo packs or reels
	Jumper wire	Reel bobbin
Throughput ^{*1}	Axial parts	8,000 cph
	Radial parts	6,000 cph
	Jumper wire	8,000 cph
Size (L x W x H)		2,600 x 1,734 x 1,710 mm

*1 The throughput shown is under optimum conditions.